

## OYB22477

•

The multi-function light barriers are through-beam sensors where multiple beams are integrated. In case of interruption of only one beam, the switching output of the receiver changes its state. The devices are used where standard through-beam sensors with only one beam are not sufficient. There are devices with beam spacing of 20, 40, 60 or 120mm and different heights available. An integrated fuzzy logic controls the transmitting power automatically.

### MECHANICAL DATA

Ambient temperature	-25 °C ... 55 °C
Degree of protection (IP)	IP65
Housing material	Aluminium
Material of optical surface	Plastic
Protected field height	460 mm
Sensor height	640 mm
Sensor length	31.25 mm
Sensor width	9 mm
With bolt mounting	Yes

### ELECTRICAL DATA

Cascadable	No
Clock control possible	No
Equipment protection class	Protection class 3
Max. output current	100 mA
No-load current, receiver	90 mA
No-load current, transmitter	90 mA
Number of output contacts with signaling function	1
Number of pins, receiver	4
Number of pins, transmitter	4
Override possible	No
Rated control supply voltage $U_s$ at DC	10 V ... 30 V
Reaction time	220 ms
Reverse polarity protection	Yes
Short-circuit-proof	Yes
Suitable for safety functions	No
Suppression possible	Yes
Type of electrical connection	Connector M8
Type of switching function	Normally open/normally closed
Type of switching output	Relay contact
Voltage type	DC

## ELECTRICAL DATA

With heater	Yes
With monitoring function of downstream devices	No
With muting function	No
With restart lock	No

## OPTICAL DATA

Beam spacing	20 mm
Number of beams	24
Protected field range	5 m
Resolution of the light curtain	20 mm
Wavelength of the sensor	880 nm

## OTHER DATA

Explosion protection category for dust	None
Explosion protection category for gas	None
Reduced resolution	No
Scope of delivery of the one-way system	Transmitter and receiver
With beam coding	Yes

## CONNECTION



**Colors:** A: 1 = BN (brown), 2 = WH (white), 3 = BU (blue), 4 = BK (black)

B: 1 = BN (brown), 2 = WH (white), 3 = BU (blue), 4 = BK (black) **Functions:** A: 1 = L+, 2 = test, 3 = L-, 4 = n. c.

B: 1 = L+, 2 = relay, 3 = L-, 4 = relay

## DIMENSIONAL DRAWING

### INSTALLATION



Mounting / Installation may only be carried out by a qualified electrician!

### DISPOSAL



### SAFETY WARNINGS

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!