

FY98C620**FILLING LEVEL SENSORS • OSCILLATION FORKS**

Filling level and level sensors operate according to different measuring principles. The selection of the sensor depends on the medium to be detected and the ambient conditions. The material flow in a vibratory bowl can be excellently queried with inductive filling level sensors whose pendulum is moved by the material in the pot. The detection of liquid or solid media is, for instance, possible with capacitive filling level sensor technology. These work according to the principle of the condensator, the medium changes the dielectricity between two electrodes. The resulting change is converted into a digital output signal. A further alternative for the detection of filling levels of conductive media is provided by conductive filling level relays. The resistance between reference and measuring electrode is determined. If a set threshold is exceeded, a relay output switches.

MECHANICAL DATA

Ambient temperature	-40 °C ... 70 °C
Degree of protection (IP)	IP67
Pressure resistance	40 bar
Probe diameter	28 mm
Type of process connection	G1 inch

ELECTRICAL DATA

Number of contacts as normally open contact	1
Number of probes	2
Rated control supply voltage U_s at DC	10 V ... 55 V
Type of electrical connection	Plug-in connection
Type of switching function	Normally open contact
Type of switching output	PNP

DIMENSIONAL DRAWING**INSTALLATION**

Mounting / Installation may only be carried out by a qualified electrician!

DISPOSAL**SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!

