

**OE120322**

**OPTICAL SENSORS • THROUGH-BEAM SENSORS RECEIVERS**

Optical sensors function contactlessly. They detect objects independent of their characteristics (e.g., shape, color, surface structure, material). The basic operating principle is based on the transmission and reception of light. There are three different versions: 1. The through-beam sensor consists of two separate devices, a transmitter and a receiver that are aligned with one another. If the light beam between the two devices is interrupted, the switching output integrated in the receiver changes its status. 2. With the retro-reflective sensor, the transmitter and receiver are located in one device. The emitted light beam is reflected back to the receiver by a reflector that is to be mounted opposite the device. As soon as the light beam is interrupted, the switching output integrated in the device changes its status. 3. With the diffuse reflection sensor, the transmitter and receiver are in one device. The emitted light beam is reflected by the object that is to be detected. As soon as the receiver detects the reflected light, the switching output integrated in the device changes its status.



**MECHANICAL DATA**

Ambient temperature (MAX)	50 °C
Ambient temperature (MIN)	-20 °C
Degree of protection (IP)	IP67
Housing coating	Nickel-plated
Housing design	Cylinder, screw-thread
Housing material	Brass
Sensor length	72 mm
Shock resistance	30 g
Thread length	40 mm
Thread pitch	1 mm
Thread size, metric	12

**ELECTRICAL DATA**

Measuring range	15 m
No-load current	10.5 mA
No-load current, receiver	10.5 mA
Number of pins	4
Operating voltage (MAX)	30 V
Operating voltage (MIN)	10 V
Rated switching distance	15000 mm
Scanning function	Light-/dark-on mode
Switching frequency	200 Hz
Type of electrical connection	Connector M12
Type of input voltage	DC
Type of switching function	Programmable/configurable
Type of switching output	PNP
Voltage type	DC

**ELECTRICAL DATA**

With LED display	Yes
With time function	No

**OPTICAL DATA**

Angle of beam spread	16 °
Light beam form	Point
Light source	Infrared light
Wavelength of the sensor	880 nm

**OTHER DATA**

Scope of delivery of the one-way system	Receiver
---	----------

**DIMENSIONAL DRAWING****INSTALLATION**

Mounting / Installation may only be carried out by a qualified electrician!

**DISPOSAL****SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!

Never use these devices in applications where the safety of a person depends on their functionality.