

#### IB180109

#### **INDUCTIVE SENSORS • WELDING PROOF**

Inductive proximity switches are contact-free sensors. They detect all conductive metals, regardless of whether they move or not. The achievable sensing range of the devices depends on the object material and its dimensions. The vibration-resistant sensors can be approached laterally or frontally. Inductive proximity switches are used for presence detection (e.g. goods carriers), positioning (e.g. dampers), counting (e.g. nuts /bolts), speed detection (e.g. for cog wheels), on conveyor systems (e.g. hose feedings) or distance measurements (e.g. press-in checking) of metallic objects.

## **MECHANICAL DATA**

Active area material of sensor	PA 6.6 (synthetic)
Ambient temperature	-25 °C 70 °C
Cable length	2 m
Degree of protection (IP)	IP67
Housing coating	Teflon coated
Housing design	Cylinder, screw-thread
Housing material	Brass
Material of cable sheath	PTFE
Mechanical mounting condition for sensor	Flush
Number of wires	3
Pressure-proof	No
Sensor length	60 mm
Thread pitch	1 mm
Thread size, metric	18

## **ELECTRICAL DATA**

Cascadable	No
Interference resistance to magnetic fields	Immune against magnetic AC-field
IO-Link compatible	No
Max. output current	200 mA
Norm measuring plate	18x18x1
Reverse polarity protection	Yes
Short-circuit-proof	Yes
Suitable for safety functions	No
Supply voltage	10 V 30 V
Switching distance	5 mm
Switching frequency	15 Hz
Type of electrical connection	Cable
Type of switching function	Normally open contact
Type of switching output	PNP
Voltage type	DC




## **ELECTRICAL DATA**

With LED display	Yes
With monitoring function of downstream devices	No

## **OTHER DATA**

Welding area	Yes
Welding-proof sensors	Yes

## **CONNECTION**



**Colors:** BN (brown), BU (blue), BK (black) **Functions:** BN = L+, BU = L-, BK = PNP NO

## **DIMENSIONAL DRAWING**

# INSTALLATION DISPOSAL



Mounting / Installation may only be carried out by a qualified electrician!



#### **SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!